




MX60MKII

COMPACT MIXING AMPLIFIER

With its 60W of power, the MX60MKII can be used in numerous commercial and residential applications. It features a built-in Bluetooth module so you can play music wirelessly from a smartphone, tablet or computer. If you prefer to play a fixed playlist of songs, you can do so via USB or microSD. The MX60MKII is equipped with a separate volume control for each input channel and is protected against short circuits and overheating.

output capacity 100V	60W
output capacity RMS 80	60W
frequency range	80Hz - 18kHz < 0,5% THD
zones	1
direct output	4-8Ω / 70V / 100V
tone control	bass & treble
built-in source	USB Bluetooth microSD
line-out	RCA
MIC input	MIC1/MIC2: 600 Ω 10 mv balanced, MIC1 (front) unbalanced
AUX input	2 RCA
priority input	MIC 1
phantom power	MIC 1, MIC 2 with DIP switches
power supply	AC100V - AC240V - DC24V
dimensions (h x w x d)	63 x 215 x 285 mm
weight	1,8kg
extra	remote control



Pleasant background music and the right ambiance in the shop, the MX60MKII makes it happen every day.

